Intellian

V100NX All New Ku-Ka Dual Band GEO/MEO/LEO 1m Maritime VSAT Terminal



I Ku-Ka Dual Band Ready

The v100NX is the Ku- to Ka-band convertible antenna that can be simply converted from Ku- to Ka-band. The reflector and radome are frequency tuned for both satellite bands, ensuring maximum performance in both bands.

I 2.5GHz Wideband Ka Ready

The v100NX uses 2.5GHz wideband Ka tuned Radome & Reflector. It provides the convenience of not having to replace the Radome and Reflector when using 2.5GHz service in the future.

I Standardized Modular Components Across NX Series

Modular components are used throughout the NX range, such as dynamic motor brakes with integrated encoders, Main Control Unit and skew assembly. Sharing common modules across Intellian's NX antenna series, the number of spare parts is reduced.

I GEO/MEO/LEO Tracking Capability

The v100NX is ready for the future. Designed with the world's most accurate satellite tracking performance with our proven tracking algorithm covering GEO, MEO and LEO constellations.

I Single Coaxial Cable

The v100NX integrates RF and power cables into one coaxial cable. A single cable carries Tx, Rx, DC power, data and reference signals between the antenna and the BDT.

New AptusNX

Intellian's all new integrated M&C platform, AptusNX provides responsive web user interface to manage and control the antenna system regardless of device types. Installation Wizard in AptusNX automates functions for system configuration so that operators are minimally involved in system installation and operation, including automatic cable loss compensation, line-up test and auto diagnostics.

V100NX All New Ku-Ka Dual Band GEO/MEO/LEO 1m Maritime VSAT Terminal

I Technical Specifications

Above	Deck	Unit

Radome Height	145.8 cm / 57.4″	
Radome Diameter	137.9 cm / 54.3″	
Reflector Diameter	105 cm / 41.3"	
Weight	113 kg / 249.1 Ibs	
Azimuth Range	Unlimited	
Elevation Range	-20° to 115°	
Cross-level Range	± 37°	
Stabilization Accuracy	0.2° peak miss-pointing @ max ship motion condition	
Motor Brake System	Dynamic Break System	
Tx Frequency	13.75 ~ 14.5 GHz Ku-band	
Tx Gain	42.0 dBi @ 14.25 GHz (excl. radome)	
Rx Frequency	10.7 ~ 12.75 GHz Ku-band	
Rx Gain	40.7 dBi @ 11.7 GHz (excl. radome)	
G/T	> 20.0 dB/K @ 12.75 GHz (Clear Sky, 30° Elevation)	
BUC Power	8W, 16W, 25W (Optional)	
LNB	Intellian PLL LNB	
Polarization	Linear, Cross & Co-pol	
Antenna Cable	Single 50ohm Coax Cable for Rx, Tx, FSK, Reference and Power from ACU to ADU	

I System Dimension



System Diagram



Antenna Control Unit

Dimensions (WxDxH)	43.1cm x 41.1cm x 4.4cm / 17" X 16.1" X 1.7"
Weight	5.2 kg / 11.5 Ibs
Display	OLED Display
Gyrocompass Interface	NMEA2000, NMEA0183
Mediator Interface	Yes
Modem Interface	Ethernet port / RS-232C,-422C / I/O Console
Modem Protocol	iDirect, Comtech, SatLink, Hughes, GILAT, Newtec
Wi-Fi Operation	Yes (w/ Wi-Fi dongle)
Management Port	Yes
Intellian LAN Port	Yes
Power Requirement	100 ~240 VAC, 50~60Hz, 4A

System Diagram (Dual Antenna)





Global HQ Innovation Center Intellian Technologies, Inc T +82 31 379 1000 F +82 31 377 6185 **APAC** Seoul Intellian Technologies, Inc. T +82 2 511 2244 F +82 2 511 2235 Americas Irvine Intellian Technologies USA, Inc. T +1 949 727 4498 F +1 949 271 4183 Toll Free +1 888-201-9223 EMEA Rotterdam Intellian B.V. T +31 1 0820 8655 F +31 1 0820 8656

©2019 Intellian Technologies, Inc. All rights reserved. Intellian and the Intellian logo are registered trademarks. v100NX and v-Series are trademarks of Intellian Technologies, Inc. in the U.S. and/or various countries. All other trademarks are the property of their respective owners. Information in this document is subject to change without notice. ISO9001 / ISO14001 Certified Intellian has more offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Intellian Website at intelliantech.com